



## QR-3051

### Features :

- ▶ Metal case
- ▶ can be installed on turnstile
- ▶ Rainproof

### Parameters :

- ▶ Recognition type: QR/Bar code Reading
- ▶ Recognition format: Full code
- ▶ Trigger mode: Automatic
- ▶ Output format: WG26/WG34/RS232/USB/RS485(the default is WG26/34, other format may be customized)
- ▶ Recognition distance: 50-200mm(depends on the size of QR code)
- ▶ Recognition precision:  $\geq 7.5\text{mil}$
- ▶ Working temperature:  $-20^{\circ} \sim 60^{\circ}$
- ▶ Environment humidity: 10%RH  $\sim$  90%RH
- ▶ Working voltage: DC5V  $\sim$  15V
- ▶ Working current:  $\leq 230\text{mA}$
- ▶ Transmission/Cabling Distance: 50m
- ▶ Material: Aluminium alloy
- ▶ Color: gold, silver color can be customized
- ▶ Dimension: 86mm\*86mm\*40mm

### **FORTUNA IMPEX PVT LTD**

P-73, Kasba Industrial Estate, Phase-2, Off E. M. Bypass, Kolkata - 700 107 (India)

☎ : 7550 670 670 ✉ : info@fortunaindia.com

🌐 : www.fortunaindia.com